

Trove1SP1 (Enclosure & Backplane)

Access and Power Integration Solutions



Altronix Trove™ enclosures and backplanes let you easily integrate Altronix power with Suprema CoreStation module access control. Trove simplifies board layout and wire management, reduces installation time and labor costs.



Trove1SP1

* Boards not included



Trove1SP1 (Trove1 Enclosure + TSP1 Backplane) Features

- Accommodates one (1) Suprema CoreStation module
- Altronix Power Supply
- Altronix Sub-Assemblies
- Includes Altronix Trove1 Enclosure and one (1) removable TSP1 backplane.

Agency Listings

UL:

UL294 - Access Control System.

cUL:

CAN/ULC - s319-05 - Electronic Access Control Systems.

CE

European Conformity.

Features

- Simplifies board layout and wire management
- Convenient knockout configuration:
 - One (1) double knockout
1.948" (1-1/2" Conduit) / 1.701" (1-1/4" Conduit).

Features (cont'd)

- Nine (9) double knockouts
1.362" (1" Conduit) / 1.115" (3/4" Conduit).
- Accommodates up to two (2) 12VDC/7AH batteries
- 16 AWG powder coated steel
- Includes cam lock, tamper switch and mounting hardware

Trove1SP1 - Dimensions (H x W x D):

18.0" x 14.5" x 4.625" (457.2mm x 368.3mm x 117.5mm)

Trove1SP1 - Weights:

Product - 15.15 lb. (6.87 kg)

Shipping - 19.05 lb. (8.64 kg)

TSP1 - Dimensions (H x W x D):

16.625" x 12.5" x 0.3125" (422.3mm x 317.5mm x 8mm)

TSP1 - Weights:

Product - 3.35 lb. (1.52 kg)

Shipping - 4.0 lb. (1.81 kg)

Access Controller Position Chart for the Following Models:

Altronix / Suprema	Pem Mounting
AL400ULXB2, AL400ULXB2V, AL600ULXB, AL600XB220, AL1012ULXB, AL1012XB220, AL1024ULXB2, AL1024XB2V, eFlow4NB, eFlow4NBV, eFlow6NB, eFlow6NBV, eFlow102NB, eFlow102NBV, eFlow104NB, eFlow104NBV, Tango1B	(A)
ACM4, ACM4CB, LINQ8PD, LINQ8PDCB, MOM5, PD4UL, PD4ULCB, PD8UL, PD8ULCB, PDS8, PDS8CB, VR6	(B)
Suprema CoreStation	(C)



